



Installation instruction - SF letters with converter box


1., Purchased parts package




lighting signage



converterbox




wiring diagram and
assembling aid




installation
drawing

2., Fastening of the letters


Single letters:



1., Adjust the drawing



2., Drill the fixing and cable
holes according to the
drawing



3., Fix the letters

Attention!

Fixing screws must not be too long -
Thread length in the letter is 5mm!

Cable feedthrough should be as big as possible.
Wire insulation at the feedthrough must not be
damaged!

Signage on substructure:

Fix the letters at the fixing ears. Look out when drilling through the profiles! Do not damage the cable!

3., Installation of the converter box

Install the box on a not too hot, preferably on a weatherproof place. Cable feedthroughs should look down.

4., Connecting of cables and power connection

Open the cover, connect the cables to the letters on the labelled terminals. Watch out for proper polarity!
Connect red cable to red terminal, black cable to black terminal. Afterwards complete power connection on the provided terminal. Pay attention to proper power supply voltage!

5., Switching-on

If all letters light properly, close converter box.